

PROJECT		


**VOLTAGE** 

**TYPE** 

### OUTDOOR TURTLE WALL FIXTURE \$33W

#### **OUTDOOR DECORATIVE EVERSTONE**





Wave Lighting's S33W was created for turtle friendly wildlife and security applications. Wave Lighting's S33W is designed for wall applications and non-corrosive mounting hardware is included.





















# LED SOURCE OPTIONS

# **LIGHTWAVE LED - LR/LT**

- 120V, 50/60 Hz
- AC Driver-On-Board Array
- Estimated 50,000 Hrs  $L_{70}$
- Low Flicker (LT models)
- Surge Supression
- Dimmable (see compatible dimmer list)
- High Efficacy LED Light Source
- 3000K or 4000K CCT; 80 or 90 CRI
- 5 Year Warranty
- Energy Star

# E26 MEDIUM BASE - LE26C/W/A

- 120V, 50/60Hz (LE26A models 120-277v)
- "Screw-In" Medium Base A19/E26 LED Lamp
- Estimated 15,000 Hrs  $L_{70}$
- Low Flicker (3K models)
- Dimmable (see compatible dimmer list)
- 3000K CCT 90CRI or 4000K CCT 80CRI
- 590nm Amber Models
- 3 Year Warranty (LE26A models 5 Year)
- LE26A models Florida Wildlife Approved
- LE26C/W models Energy Star

# **SPECIFICATIONS**

- · Black, White, & Bronzestone
- Nylon Non-Corrosive Hardware Included
- No Insignia, Lighthouse, Turtle or Custom InsigniaO
- Wall Mount Only
- Oceanside Approved
- Minimum Starting Temp -20°F
- Meets FWC Standards for Beachfront, Turtle Safe Lighting
- UL Listed for Wet Locations
- Composite Construction
- Non-Corrosive







### **GUIDE CODE: S33WL-LE26A-WH**

### **CALL FOR PHOTOMETRIC INFORMATION**

ITEM#	INSIGNIA	LIGHT SOURCE	сст	COLOR
N-No Insignia L-Lighthouse T-Turtle		E26 MEDIUM BASE	<b>C</b> -4K	<b>BK</b> -Blackstone
	(1) 60W MAX Medium Base <b>LE26</b> -9.5W 800lm (E26 LED Lamp) ★ ★	<b>W</b> -3K	WH-Whitestone BZ-Bronzestone	
	120V LIGHTWAVE LED			
	<b>LR12</b> -13W 1000lm 80CRI ★ <b>LT12</b> -12W 1040lm 90CRI			
		120-277V E26 AMBER LED		
		<b>LE26A</b> -11W 336Im (E26 LED Lamp) +	596nm	

<sup>+</sup> Lamp included. ★Energy Star qualified product. Consult factory for details. Florida wildlife certified lighting.