

PROJECT

TYPE

VOLTAGE

ACORN POST TOP FIXTURE 9018



SPECIFICATIONS

- Cast Aluminum or Polycarbonate Fitters
- Black, White, or Bronze (Aluminum Only)
- Post Mount Only
- Polyethylene Acorn Diffuser
- Opal Textured Diffuser Options
- UL Listed For Wet Locations

OUTDOOR DECORATIVE

Wave Lighting's Acorn Post Top Fixture is ideal for any outdoor patio or walkway. This fixture is available in incandescent with A19 LED lamp option and is easily relamped via 2 screws in fitter. Wave Lighting's Acorns fit on a 3" diameter pole (sold separately) mounting hardware is included.

LED SOURCE OPTIONS

LIGHTWAVE LED - LR/LT

- 120V, 50/60 Hz
- AC Driver-On-Board Array
- Estimated 50,000 Hrs L_{70}
- Low Flicker (LT models)
- Surge Supression
- Dimmable (see compatible dimmer list)
- High Efficacy LED Light Source
- 3000K or 4000K CCT 80 or 90 CRI

• 5 Year Warranty E26 MEDIUM BASE - LE26

- 120V, 50/60Hz
- "Screw-In" Medium Base A19/E26 LED Lamp
- Estimated 15,000 Hrs L₇₀
- Low Flicker (3K models)
- Dimmable (see compatible dimmer list)
- 3000K CCT 90CRI or 4000K CCT 80CRI
- 3 Year Warranty
- E39 RETRO-FIT LED LC
- 120-277V, 50/60Hz
- 250W Metal Halide Equivalent Lamp
- E39 Mogul Base Socket
- Estimated 50,000 Hrs L_{70}
- Surge Supression
- Available in 4000K CCT 80CRI
- Type 3, Type 5, or Dark Sky Distribution
- 5 Year Warranty

CALL FOR PHOTOMETRIC INFORMATION

ITEM #	LENS		сст	FITTER MATERIAL	OPTIONS
	POLYETHYLENE Opal Textured	E26 MEDIUM BASE (1) 75W MAX Medium Base LE26-9.5W 800Im (E26 LED Lamp) +	С-4К W-3К	CAST ALUMINUM Black WH-White BZ-Bronze POLYCARBONATE BP-Black WP-White	MG -E39 Mogul Socket
		120V LIGHTWAVE LED			
		LR12-13W 1000lm 80CRI LR15-15W 1400lm 80CRI LR22-23W 1900lm 80CRI LT12-12W 1040lm 90CRI LT15-16W 1400lm 90CRI LT22-24W 2020lm 90CRI			
		E39 RETRO-FIT LED 120-277V			
		LC5-24W 3120lm, Type 5 + LC3-20W 3000lm, Type 3 + LCD-24W 2400lm, Dark Sky +			

+ Lamp included.

GUIDE CODE: 9018-LR12C-BP